Apple II SCSI Card: Interrupt Problem (11/96)

Revised: 11/21/96
Security: Everyone

Apple II SCSI Card: Interrupt Problem (11/96)

===

Article Created: 26 November 1986
Article Reviewed/Updated: 15 November 1996

TOPIC ---

This article discusses a potential problem with the Apple IIGS, Apple II SCSI
card and programs using interrupts.

DISCUSSION ---

Apple IIGS system crashes may occur with programs using interrupts during access
of SCSI disk drives connected to the Apple II SCSI card. Once interrupts are
enabled, it is possible an interrupt may occur during a SCSI drive data
transfer. Programs initiate data transfer by passing control to the SCSI card.

The SCSI card firmware places code in its own stack for executing. If taking an
interrupt also places code on the same stack it may wipe out some or all of the
previous SCSI firmware code. Returning from the interrupt, returns to the
portion of the stack corrupted by the interrupt, which results in some kind of
unidentifiable system crash.

Crashes are possible if BOTH of the following conditions apply:

- The SCSI card is used with an interrupt driven program, like AppleTalk.

- This application program calls the SCSI card directly, NOT using ProDOS.

To work around this possibility, make sure your applications use ProDOS to
handle any interrupts. This may decrease SCSI disk data transfer rates but will
help reduce system crashes.

Article Change History:
15 Nov 1996 - Reviewed for technical accuracy, revised formatting.

Copyright 1986-96, Apple Computer, Inc.

Tech Info Library Article Number:2097